

FOXTAM ELECTRICAL MEASUREMENT TRANSDUCERS

PRODUCT
GROUP
GG

GENERAL SPECIFICATIONS & DIMENSIONS

■ OUTPUT

Response time:	<400mSec
Warm up time:	<15 mins
Output ripple:	1% peak full scale
Long term drift:	+/- 0.25% per year non cumulative
Maximum load:	0-1mA 10 KOhm max 0-2.5mA 6 KOhm max 0-5mA 3 KOhm max 0-10mA 1.5 KOhm max 0-20mA & 4-20mA 750 Ohm max
Adjustment:	Self powered voltage & current transducers have an adjustable span only All other transducers have an adjustable zero & span

■ AUXILIARY SUPPLY


AC:	24 / 110 / 230 / 415V others on request
DC:	24 / 48 / 110V
Tolerance:	+/- 20%
Consumption:	4VA / W (combined Watt / VAr transducers 7VA / W)

■ EMC COMPLIANCE

Directive 89/36/EEC: Electrostatic discharge IEC801.2 (8KV)
Electromagnetic fields IEC801.3 level 3
Fast transient bursts IEC801.4 level 4
Surge withstand IEC255-5

■ ENCLOSURE

Material:	Grey ABS plastic with finger proof terminal covers
Isolation:	4KV rms 50Hz for 1 min (to IEC414) between input / output / case / auxiliary supply 1KV DC / 600VAC between outputs on combined Watt / VAr transducers
Mounting:	35mm Din rail (DIN-EN 50022)
CE Marked:	Yes



See individual transducer data sheets for unit specific specification details

AC VOLTAGE TRANSDUCERS

TYPE: FOX.TR.AU

DESCRIPTION



PRODUCT
GROUP
GG

Foxtam AC voltage transducers can measure voltage either directly (max 600VAC) or via the secondary of a voltage transformer. The transducer converts the AC input voltage to an isolated analogue DC mA or DC voltage analogue signal output, directly proportional to the input. The 4KV isolated output signals can be utilised for many applications and can be fed into analogue meters, digital meters, PLC's or BMS systems.

Transducer types include:-


Self powered - The lower cost option where no auxiliary supply is required but at least 10% of the input range is required to start generating an accurate output. Self powered units can only give a zero based output, hence a 4-20mA output is not possible. Self powered units also have an enhanced burden on the input (circa 3VA).

Powered – An auxiliary supply is required, these transducers can be used accurately down to 0% of the input range. A wide choice of outputs are possible including 4-20mA.

Powered TRMS – As per the standard powered transducer but with enhanced measuring technology, typically used for the accurate measurement of distorted waveforms. TRMS versions are also suited for use on high frequency circuits between 40 to 500Hz.

SPECIFIC SPECIFICATIONS

Accuracy:	Class 0.25
Input voltage:	0-50V...600VAC direct VT ratio specify
Overload:	1.2 x U_n continuous 1.5 x U_n for 1 sec
Working range:	0-120% U_n (powered units) 10-120% U_n (self powered units)
Frequency:	50Hz or 60Hz 40-500Hz (TRMS units)
Input burdens:	<0.2VA (powered units) <3VA (self powered units)
Case size:	1



ORDERING INFORMATION

TYPE	INPUT RANGE	OUTPUT	AUX SUPPLY
FOX.TR.AU / Self powered	0-50...600VAC direct*	0-1mA	24VAC
FOX.TR.AU / Powered	VT ratio	0-2.5mA	63VAC
FOX.TR.AU / Powered TRMS	Expandable input***	0-5mA	110VAC
	Suppressed zero input***	0-10mA	230VAC
		0-20mA	415VAC
		4-20mA**	24VDC
		0-1VDC	48VDC
		0-5VDC	110VDC
		0-10VDC	

*Specify exact direct input range required, recommended standard ranges 0-150V, 0-300V, 0-500V

**Not possible on self powered units

***Suppressed zero and expandable input versions are possible on powered units ie, a +/- % deviation around a nominal point 184-230-276V giving for example say 0-5-10VDC or 4-12-20mA output. Consult office for advice